

WiringPi: GPIO Pin Numbering Tables

<https://wiki.odroid.com/odroid-xu4/hardware/>

ODROID-XU3/XU4: Shift-Shield 40 Pin GPIO connector(CON3)						
WiringPi Pin	Native GPIO	Name	Header		Name	WiringPi Pin
		3.3v	1	2	5v	
8	209 (GPB3.2)	SDA1	3	4	5v	
9	210 (GPB3.3)	SCL1	5	6	0v	
7	18 (GPX1.2)	GPIO7	7	8	TxD	172 (GPA0.1) 15
		0v	9	10	RxD	171 (GPA0.0) 16
0	174 (GPA0.3)	GPIO0	11	12	GPIO1	173 (GPA0.2) 1
2	21 (GPX1.5)	GPIO2	13	14	0v	
3	22 (GPX1.6)	GPIO3	15	16	GPIO4	19 (GPX1.3) 4
		3.3v	17	18	GPIO5	23 (GPX1.7) 5
12	192 (GPA2.7)	MOSI	19	20	0v	
13	191 (GPA2.6)	MISO	21	22	GPIO6	24 (GPX2.0) 6
14	189 (GPA2.4)	SCLK	23	24	CE0	190 (GPA2.5) 10
		0v	25	26	CE1	25 (GPX2.1) 11
30	187 (GPA2.2)	SDA2	27	28	SCL2	188 (GPA2.3) 31
21	28 (GPA2.4)	GPIO21	29	30	0v	
22	30 (GPX2.6)	GPIO22	31	32	GPIO26	29 (GPX2.5) 26
23	31 (GPX2.7)	GPIO23	33	34	0v	
24	PWR_ON (INPUT)	GPIO24	35	36	GPIO27	33 (GPX3.1) 27
25	ADC.AIN0	GPIO25	37	38	GPIO28	1.8V Ref Out 28
		0v	39	40	GPIO29	ADC.AIN3 29
WiringPi Pin	Native GPIO	Name	Header		Name	WiringPi Pin